



>THIS IS THE WAY

>THIS IS NORTEL™

Technical Bulletin

Nortel Business Communications Manager 200 and Business Communications Manager 400

Technical Specifications

Base unit

Physical dimensions	BCM400	BCM200
Depth	18.3 in.; 46.5 cm	18.3 in.; 46.5 cm
Width	17.5 in.; 44.5 cm	17.5 in.; 44.5 cm
Height	7.1 in.; 18.0 cm	3.5 in.; 9.0 cm
Weight	Std. 28.4 lbs; 35.9 Kg Redundant 37.1 lbs; 44.6Kg	Std. 19.75 lbs; 26.4 Kg

Components	BCM400	BCM200
Media Bay Module Bays	Four	Two
CPU Processor	Intel Celeron 1.2 GHz	Intel Celeron 1.2 GHz
Memory (RAM)	256 MB SDRAM	256 MB SDRAM
Hard Drive	20 GB EIDE	20 GB EIDE

System Status LEDs

Power status, Hard drive activity, System status, PCI device monitoring (MSC, WAN, NIC 1, NIC 2), Chassis/CPU temperature, Fan activity reset button.

The System Status Monitor Card controls and monitors fans, power supply, chassis temperature and OS status.

Mounting options

Rack-mount (standard 19-inch rack); Stand-alone (feet included); Wall-mount (optional wall mount bracket available separately)

Power supply specifications

Standard power supply	Redundant power supply (BCM400 only)
Auto-sensing	Auto-sensing
300 Watts	350 Watts
90/264 VAC	90/264 VAC
6.0 A/3.0 A	7.0 A/3.5 A
60/50 Hz	60/50 Hz

Environmental specifications

Operating temperature	32° to 104°F; 0° to 40°C
Operating humidity	10% to 90% relative humidity, non-condensing
Storage temperature	-67° to 158°F; -55° to 70°C
Storage humidity	Up to 95% relative humidity

Mechanical requirements

NEBS (GR-63-CORE) compliant for Transportation and Operational Vibration and Package Drop Shock resistance per IEC 68-2-27, Transportation Bounce to IEC 68-2-55 and Unpackaged Drop to ISTA Project 1A.

Regulatory compliance

Electromagnetic emissions

Radiated Air	Australia AS3548 Class A North America CISPR22 Class A United Kingdom EN55022 Class A
Conducted Power Leads	Australia AS3548 Class A North America CISPR22 Class A United Kingdom EN55022 Class A

Immunity (Narrow band RF interference)

Radiated	North America customer driven (based on EN 61000-4-3) United Kingdom/International EN55024 : 1998
Conducted	North America customer driven (Based on EN 61000-4-6) United Kingdom/International EN55024 : 1998

Immunity to electrostatic discharge

Indirect	No functional impairment up to +/- 15 kV No damage up to +/- 20 kV
Direct	Un-mated I/O ports and connectors, No damage up to +/- 5 kV Mated connector and cords, No functional impairment up to +/1 15 kV, No damage up to +/1 15 kV

Network protection

Australia TSO38/31/03/04/01
EU CTR12/13/3/4/21
North America/CALA FCC Part 68, CS 03 Issue 8

Safety and surge/transient

Australia TSO38/31/03/04/01, ACA TSO01, AS/NZS 3260
CALA/APAC except Australia EN 60950 (with national deviations),
CSA 22.2 No.950/UL 60950
North America UL1950 Ed.3, CSA C22.2 No. 950-95, UL 60950
EU CTR12/13/3/4/21, EN 60950 (with national deviations)
United Kingdom EN60950

Telephony components

Media Services Card (BCM-MSC)

One 8-pin modular jack (RJ-45) connection for Expansion Chassis
(Only on BCM400 not BCM200)

Four 3.5 mm (1/8 inch) standard miniature stereo (3-conductor)
Safety Extra Low

Voltage (SELV) jacks for auxiliary ringer, page relay, page output, and
music on hold

Auxiliary ringer switch capacity of 50mA (non-inductive) at 40 V
(maximum)

Page Relay switch capacity of 50mA (non-inductive) at 40 V (maximum)

Page Output 600 ohms impedance

Music on hold mono input

Media Services Processor Expansion Card slots
BCM400—four slots, two equipped
BCM200—two slots, one equipped

Supports maximum of 8 DS-30s. Allows 2/6 and 3/5 IP/TDM Splits.

Media Bay Modules features

16 Stn Digital Station Media Bay Module+ (DSM 16+)

- One Amphenol (male) connector (25 pair)
- Individual interfaces are current connector (25-pair); limited to 80 mA
- 16 digital phone ports
- Two LEDs: Power, Status
- Utilizes 1/2 DS-30 (with DIP switch set appropriately)

32 Stn Digital Station Media Bay Module+ (DSM 32+)

- Two Amphenol (male)
- Individual interfaces are current connectors (25 pair); limited to 80 mA
- 32 digital phone ports
- Two LEDs: Power, Status
- Utilizes 1 DS-30 (with DIP switch set appropriately)

8 Stn Analog Station Media Bay Module+ (ASM 8+)

- One Amphenol (male) connector (25 pair)
- Maximum modem connection speed: 28.8 Kbps
- 8 analog phone ports
- Approved for OPX use in US, CA, and UK
- Loop length 26G 2600 ft, 24G 4000ft; 22G 6500 ft
- Disconnect supervision—850 Ms. Momentary Disconnect
- Message Waiting Indication—NA 120V. 600 ms On and 1000 ms Off.
UK 90V constant On
- Calling Line Identification (CLID) Name and Number per Bell 202
standard, NA only
- Two LEDs: Power, Status
- Utilizes 1/4 DS-30 (with DIP switch set appropriately)

Digital Trunk Media Bay Module (DTM)

- One 8-pin RJ-45C modular jack
- T1 trunk interface with integrated CSU
- 24 B channels with T1 interface (supports DSX-1 and DS1 interfaces)
- 23 B channels with North American PRI interface
- LEDs: Power, Status, In-service, Loop-back, Test, Receive Alarm,
Receive Error, Transmit Alarm, Transmit Error
- 30 digital channels with ETSI PRI Interface
- Utilizes 1 (one) DS-30

Digital Drop and Insert MUX Media Bay Module (DDIM)

- One 8-pin RJ-45C modular jack
- T1 trunk interface with integrated CSU
- 24 B channels with T1 interface (supports DSX-1 and DS1 interfaces)
- LEDs: Power, Status, In-service, Loop-back Test, Receive Alarm,
Receive Error, Transmit Alarm, Transmit Error
- LEDs: Transmit, Receive, RTS, CTS, DCD, DSR, TM
- V.35-DB26 miniature connector
- Cables: V.35, BCM WAN, Nortel Routers, DB-60 cable
- Utilizes two DS-30s

Basic Rate Interface Media Bay Module (BRIM S/T)

- Four modular RJ-45 jacks
- Supports four S/T interfaces (8 B-channels)
- T-interface to connect to a NT1 device or an S-interface to connect
ISDN terminals.
- Supports ETSI and National ISDN BRI
- Two LEDs: Power, Status
- Utilizes 1/3 DS-30

Global Analog Trunk Module (GATM 4)

- One Amphenol (male) connector for analog North American, UK
and Australia Standard
- Four loop start CLASS/CMS lines plus one auxiliary port for V.90
modem, fax, analog telephone connection, or Power Fail Transfer
- Two LEDs: Power, Status
- Utilizes 1/4 DS-30

Global Analog Trunk Module (GATM 8)

- One Amphenol (male) connector for analog North American, UK and
Australia Standard
- Eight loop start CLASS/CMS lines plus one auxiliary port for V.90
modem, fax, analog telephone connection, or Power Fail Transfer
- Two LEDs: Power, Status
- Utilizes 1/2 DS-30

4x16 Combo Module (4 Caller ID trunks + 16 Station sets, CMB4x16)

- Modular RJ-11 jacks to support four loop start CLASS/CMS lines plus
one auxiliary port for V.90 modem, fax, analog telephone connection,
or Power Fail Transfer
- One Amphenol (male) connector (25 pair) to support 16 digital
phone ports
- Individual interfaces are currently limited to 80mA
- Two LEDs: Power, Status
- Utilizes 1 1/4 DS-30s

Fiber Expansion Media Bay Module (FEM)

- Six fiber ports
- Connects up to six Norstar* fiber-based trunk or station modules
- Two LEDs: Power, Status
- Utilizes 1 DS-30 for each Norstar fiber trunk or station module
connected (up to 6)

DECT Mobility Media Bay Module (DECT8, A-Law & Mu-Law— Europe & Taiwan only)

- Four BRI ISDN-S loops
- Supports up to 8 radio base stations through eight RJ-45 connectors
- Each BCM system can support one DECT module with a maximum of
32 DECT handsets
- Each DECT radio base station supports up to 4 simultaneous calls
- A maximum of 8 simultaneous calls can be established between
DECT handsets and the BCM core
- Available in either A-Law or Mu-Law companding law version of
firmware
- Two LEDs: Power, Status
- Utilizes 1 DS-30

Data networking components

Embedded v.92 Modem (North America only)

- North America and UK only for Dial Backup or Remote Admin
- V.92 56 Kbps ITU standard
- V.34 33.6 Kbps ITU standard
- RJ-11 connector
- V.42/MNP 2-4 error control
- V.42/MNP 5 data compression
- Capable of receiving data at 56 kbps and sending data at 31.2 kbps

10/100 Ethernet LAN interface

- 10/100BASE-T Ethernet ports (on board the mainboard)
- Supports IEEE 802.3 Ethernet frame format
- Uses Carrier Sense Multiple Access with Collision Detection (CSMA/CD)
- 100BASE-TX with RJ-45 connector
- 10/100 Auto-sensing
- Full-duplex support
- Fast LAN to LAN routing
- LAN traffic smoothing
- IPX support
- PPPoE (enabled using keycode)

WAN interface

Two port PCI card (field installable)

- Each port can be independently configured to Frame Relay or PPP
- STAC compression is available
- One serial sync port (V.35) and one T1 port with integrated CSU and DSU connectivity - N.A. only
- Two serial ports (V.35) - N.A. only
- Two serial ports (V.35 and X.21) - EMEA only

ISDN via MBMs

- Up to 16 ISDN B-channels
- (PRI or BRI) (optional)
- Dial on demand, Persistent, or WAN Backup
- MLPPP

Expansion Cabinet (BCM400 and BCM1000 only)

Connections

- Six Media Bay Module slots
- An 8-pin modular DS256 connector for the interface to the Business Communications Manager base unit (5 meter cable)

Standard Expansion Cabinet

Depth 18.3 in.; 46.5 cm

Width 17.5 in.; 44.5 cm

Height 5.4 in.; 13.6 cm

Expansion Cabinet with no Media Bay Modules 24.75 lb.; 11.25 kg

Expansion Cabinet with six Media Bay Modules 39 lb.; 17.75 kg

Redundant Expansion Cabinet (redundant power supply and fans)

Depth 20 in.; 53.8 cm

Width 17.6 in.; 44.6 cm

Height 5.4 in.; 13.6 cm

Expansion Cabinet with no Media Bay Modules 31.9 lb.; 14.5 kg

Expansion Cabinet with 6 Media Bay Modules 46.2 lb.; 21 kg

Power requirements

Standard Power Supply

Auto-sensing

300 Watts

90/264 VAC

6.0 A/3.0 A

60/50 Hz

Redundant Power Supply

Auto-sensing

350 Watts

90/264 VAC

7.0 A/3.5 A

60/50 Hz

Environmental ranges

Operating temperature 32° to 104°F; 0° to 40°C

Operating humidity 10% to 90% relative humidity, non-condensing

Storage temperature -67° to 158°F; -55° to 70°C

Storage humidity Up to 95% relative humidity

Mounting options

Rack-mount (standard 19-inch rack); Stand-alone (feet included); Wall-mount (optional wall mount bracket available separately)

Telephones and Adapters

Station Sets

Business Series

North America	Dimensions (Inches)	Loop Length (26G)	With SAPS sets
T7100	8.1D x 7Wx3.5H	1,000 ft.	2,600 ft.
T7208	8.1D x 7.7Wx3.5H	1,000 ft.	2,600 ft.
T7316E	8.1D x 10.3Wx3.5H	1,000 ft.	2,600 ft.
T24 KIM	7.7D x 3.6Wx3.4H	Connects to T7316E	
NACU	12.5 x 12Wx2H	1,000 ft.	2,600 ft.

IP Stations

- Nortel IP Phone 2004
- Nortel IP Phone 2002
- Nortel IP Phone 2001
- Nortel IP Softphone 2050 (PC or Laptop)

T24 Kim—requires T7316E

T24 EKIM (Enhanced KIM—used as CAP)—max. 12 positions per system; max 4 EKIMs per position

T24 OKIM (Ordinary KIM—used for answer/DSS/BLF)—unlimited per system; max 4 OKIMs without power supply per position; max 9 OKIMs with power supply per position

Mobility—Symbol VoIP Wireless 802.11B

NetVision Phone (Wireless VoIP)

DataVision Phone (Wireless VoIP with Integrated Bar Code Scanner)

Mobility—Cordless

T7406: 3 handsets per basestation, 2 basestations per system

Accessories

BST Doorphone

Norstar Audio Conferencing Unit (NACU)

Station Auxiliary Power Supply (SAPS)

ATA-2 Analog Terminal Adapter (separate models for NA, Europe and Australia)

In the United States:

Nortel
35 Davis Drive
Research Triangle Park, NC 27709 USA

In Canada:

Nortel
8200 Dixie Road, Suite 100
Brampton, Ontario L6T 5P6 Canada

In Caribbean and Latin America:

Nortel
1500 Concorde Terrace
Sunrise, FL 33323 USA

In Europe:

Nortel
Maidenhead Office Park, Westacott Way
Maidenhead Berkshire SL6 3QH UK

In Asia Pacific:

Nortel
Nortel Networks Centre
1 Innovation Drive
Macquarie University Research Park
Macquarie Park NSW 2109 Australia
Tel: +61 2 8870 5000

In Greater China:

Nortel
Sun Dong An Plaza
138 Wang Fu Jing Street
Beijing 100006, China
Phone: (86) 10 6510 8000

Nortel is a recognized leader in delivering communications capabilities that enhance the human experience, ignite and power global commerce, and secure and protect the world's most critical information. Serving both service provider and enterprise customers, Nortel delivers innovative technology solutions encompassing end-to-end broadband, Voice over IP, multimedia services and applications, and wireless broadband designed to help people solve the world's greatest challenges. Nortel does business in more than 150 countries. For more information, visit Nortel on the Web at www.nortel.com.

For more information, contact your Nortel representative, or call 1-800-4 NORTEL or 1-800-466-7835 from anywhere in North America.

This is the Way. This is Nortel, Nortel, the Nortel logo, the Globemark and Norstar are trademarks of Nortel Networks. All other trademarks are the property of their owners.

Copyright © 2005 Nortel Networks. All rights reserved. Information in this document is subject to change without notice. Nortel assumes no responsibility for any errors that may appear in this document.

